

# Print Utility for iOS Operating Environment

## Operating Environment of Print Utility for iOS

Item	Description
Network Protocol	LPD
Supported Models / Supported Operating System	iPad (4th generation) or later, iPad mini 2 or later, iPhone 5 or later and iPod touch (6th generation) or later iPad/iPhone/iPod touch iOS 10.0 or later *1
Supported Languages	English, Chinese (Simplified / Traditional), Korean, Japanese, Thai, Vietnamese
Features	Printing web pages Printing from photo album Printing photos taken by the internal camera Linking with Cloud Service Hub Printing DocuWorks/PDF documents by using DocuWorks Viewer Light for iPhone/iPad in tandem Working with ApeosWare Management Suite Server-less On-Demand Print Scan from scanner
Print settings	<b>Printing photo/image/ website</b> Specify the number of copies with 1 / 2 / 3 / 4 / 5 (Max 99) Paper size: A3, A4, Letter, 4 x 6" (101.6 x 152.4 mm), 2L-size (127 x 178 mm), Postcard (100 x 148 mm) Image orientation: Portrait / Landscape Output Color: On / Off 2-sided print: Off / On Pages Per Sheet: 2 Pages Up / 4 Pages Up / 8 Pages Up / 16 Pages Up / 32 Pages Up Stapling: Off / 1 Staple Top Left Paper tray: Automatically Select / Bypass tray Paper type: Plain / Heavyweight / Heavyweight Reload Authentication and Accounting
	<b>For PDF/ DocuWorks documents</b> Specify the number of copies with 1 / 2 / 3 / 4 / 5 (Max 99) Paper size: Same as Paper Size, A4, A3, A5, B4, B5, Letter, Legal, 11 x 17", Postcard (100 x 148 mm) Collated: On / Off Output Color: On / Off 2-sided print: 1sided Print / 2sided Print / 2sided, Flip on short Edge Pages Per Sheet: 2 Pages Up / 4 Pages Up Stapling: Off / 1 Staple Top Left Paper tray: Automatically Select / Bypass tray Authentication and Accounting
Scanner settings	[Scan Size] A4 / Letter [Resolution] 200 dpi / 300 dpi [Image Type] Full Colour / Grayscale [File Format] JPEG / PDF / DocuWorks
Printer settings	Specifying an IP address directly *2 Searching for a printer by using Bonjour *3 *4

- \*1: Use of the latest version is recommended.
- \*2: An IP address and port number must have been specified on the multifunction printer or printer.
- \*3: An IP address and port number must have been specified on the multifunction printer or printer, and Bonjour must be running.
- \*4: Search with Bonjour is not available when accessing from the secondary Ethernet of MFD.